

**DATA GENERAL CORPORATION**  
SOUTHBORO, MASSACHUSETTS 01772

# WIRE RUN LIST

THIS DRAWING AND SPECIFICATIONS, HEREIN, ARE THE PROPERTY OF DATA GENERAL CORPORATION AND SHALL NOT BE REPRODUCED OR COPIED OR USED IN WHOLE OR IN PART AS THE BASIS FOR MANUFACTURE OR SALE OF ITEMS WITHOUT WRITTEN PERMISSION.

Title Interconnection Cables: PS/Bk Pnl, Power Switch, LCD, XFMR/ L Filter, Monitor, P/S	Sheet 1 of 1	SIZE A	Drawing No. <b>008 000931</b>	Rev. <b>05</b>
--	--------------	--------	----------------------------------	-------------------

Drawn T. Vetter 5/7/76	Checked	Next Assy Drawing No. 6052,53	Model	Schematic Reference No.
Engineer Alan Elliott			Approved Alan Elliott	

REVISIONS				
REV.	DESCRIPTION	DRFTG.	APP. BY	DATE
00	Released per ECO B035			6/76
01	ECO B068	AC	AE	9/76
02	ECO 6505B	AC	AE	1/78
03	ECO 7163	AC	AE	
04	ECO 7490	AC	RP	8/78
05	ECO 7503B		RP	3/79

NOTES: 1. \* wires 9 & 10 stripped and tinned for attachment to speaker.

WIRE	FROM	TO	WIRE	FROM	TO	WIRE	FROM	TO	WIRE	FROM	TO	WIRE	FROM	TO
1	PWR SW LOWER 1	J24	12	J10-S	J29-6	23	Monitor R Pane Chassis	R Pane Lug	34	L/F-C	Trans #3	45		
2	PWR SW LOWER 2	J25	13	J10-6	J29-9	24	Fuse Holder	J27	35	L/F-A	Trans #4	46		
3	PWR SW UPPER 1	J26	14	J10-A	J13-1	25	J16-8	Trans #9	36	L/F-E	Trans #5	47		
4	PWR SW UPPER 2	FUSE HOLDER	15	J10-E	J29-10	26	J16-12	Trans #12	37	Speaker Gnd	Trans #6 (SH)	48		
5	POT CTR LUG	J28-1	16	J10-F	J29-1	27	J16-4	Trans #11	38	Speaker Gnd	Trans FLUX SH'LD	49		
6	POT RT LUG	J28-4	17	J16-1	J8-6	28	J16-10	Trans #13	39	J17-1	Trans #14	50		
7	POT LT LUG	J28-3	18	J16-7	J8-5	29	J16-9	Trans #7	40	J17-2	Trans #15	51		
8	J10-1	J13-2	19	J16-3	J8-4	30	J16-5	Trans #8	41			52		
9	J10-2	SPKR*	20	J16-6	J8-1	31	J16-11	Trans #10	42			53		
10	J10-3	SPKR*	21	J16-2	J8-3	32	L/F-D	Trans #1	43			54		
11	J10-4	J29-8	22			33	L/F-F	Trans #2	44			55		