

```

*****
*****
*                                     *
*                                TECH TIP 107                                *
*                                     *
*****
*****
Category::Controllers                Product::295A/295C
Reference::295A to 295C Conversion/ 295C Notes
Submitted by::Robert Shaffer        Date::August 20,1993
*****

```

295C Notes:

- 1) To run a Fujitsu 2351 disk as a single disk with 1684 cylinders, you need at least rev. 0B proms.

295A to 295C CONVERSION

- 1) Upgrade proms to 0B (7 proms)
- 2) lift 3C-12 (74LS74)
run wire from 3C-12(pin) to 3K-6 (74LS00)
- 3) lift 1D-11 (74LS74)
run wire from 1D-11(pin) to 3E-2 (74LS02)
- 4) run wire from PIN 7 of resistor pack beside the BANK SELECT switch to 3G-10 (74LS08)
- 5) lift 3M-12 (AM2602)
run wire from 3M-12(pin) to 8P-12 (74LS74)
- 6) lift 3P-1 (74LS04)
lift 2N-3 (74LS00)
run wire from 3P-1(pin) to 2N-3(pin) to 2S-2 (74LS08)
- 7) cut etch at bottom left corner (edge connector toward you) that comes from A6 BUT is on the TOP side of the board.
- 8) cut etch in top left side of board that comes from 11A-9 to a feedthru under the cap to the left of 11A.
- 9) run a wire from A6(feedthru) to 11A-9

TOP OF BOARD

